

Perturbation Analysis of Orthogonal Matching Pursuit

Jie Ding, Laming Chen, and Yuantao Gu

Abstract—Orthogonal Matching Pursuit (OMP) is a canonical greedy pursuit algorithm for sparse approximation. Previous studies of OMP have mainly considered the exact recovery of a sparse signal x through Φ and $y = \Phi x$, where Φ is a matrix with more columns than rows. In this paper, based on Restricted Isometry Property (RIP), the performance of OMP is analyzed under general perturbations, which means both y and Φ are perturbed. Though exact recovery of an almost sparse signal x is no longer feasible, the main contribution reveals that the exact recovery of the locations of k largest magnitude entries of x can be guaranteed under reasonable conditions. The error between x and solution of OMP is also estimated. It is also demonstrated that the sufficient condition is rather tight by constructing an example. When x is strong-decaying, it is proved that the sufficient conditions can be relaxed, and the locations can even be recovered in the order of the entries' magnitude.

Index Terms—Orthogonal Matching Pursuit (OMP), Restricted Isometry Property (RIP), Compressed Sensing (CS), support recovery, strong-decaying signals, general perturbations.

I. INTRODUCTION

FINDING the sparse solution of underdetermined linear equation

$$y = \Phi x \quad (1)$$

is one of the basic problems in some fields of signal processing, where $y \in \mathbb{C}^m$ and $\Phi \in \mathbb{C}^{m \times n}$ with $m < n$. The basic problem (1) has arisen in many applications, including Sparse Component Analysis (SCA) [1], [2] and Blind Source Separation (BSS) [3], [4]. Since the introduction of Compressed Sensing (CS) [5]–[8], the problem (1) has received significant attention in the past decade. In the field of CS, y denotes the measurement vector, Φ is called the sensing matrix, and x is the sparse or almost sparse signal to be recovered.

Various algorithms have been proposed to recover x . They roughly fall into two categories:

Convex relaxation: Based on linear programming technique, finding the sparsest solution to (1) can be relaxed to a convex optimization problem, also known as Basis Pursuit (BP) [6]. Algorithms used to complete the optimization include Interior-point Methods [9], Projected Gradient Methods [10], and Iterative Thresholding [11].

Greedy pursuits: These algorithms build up an approximated set of nonzero locations by making locally optimal

choices in each iteration. Several popular ones are Orthogonal Matching Pursuit (OMP) [12]–[14], Regularized Orthogonal Matching Pursuit (ROMP) [15], Compressive Sampling Matching Pursuit (CoSaMP) [16], Subspace Pursuit (SP) [17], and Iterative Hard Thresholding (IHT) [18].

For the scenario of no perturbations, the recovery process can be formulated as

$$(N_0) \quad \hat{x} = R(y, \Phi, \dots),$$

where $R(\cdot)$ denotes the process of a recovery algorithm, with the inputs listed in the following brackets, and $\hat{x}$ denotes the output, i.e. the approximation of the original sparse signal x . Process of (N_0) is non-perturbed, thus sparse signal can be exactly recovered under suitable conditions. For example, under certain conditions, BP [19], [20], OMP [21]–[27], ROMP [15], CoSaMP [16] and SP [17] all guarantee exact recovery of x .

In practical applications, the measurement vector y is often contaminated by noise. Thus a perturbed measurement vector in the form of

$$\tilde{y} = y + b \quad (2)$$

is considered, where b denotes measurement perturbation. In such scenario, the recovery process can be formulated as

$$(N_1) \quad \hat{x} = R(\tilde{y}, \Phi, \dots).$$

Plentiful studies of recovery algorithms including BP [19], [28]–[31], OMP [25], [26], [28], [31], [32], ROMP [33], CoSaMP [16], SP [17], IHT [18], and other [34] have considered the recovery accuracy in (N_1) process. Define the support set $\text{supp}(\cdot)$ as the set composed of the locations of all nonzero entries of a vector. It has been shown that OMP will exactly recover the support set of a sparse signal x from the perturbed observation vector, i.e. $\text{supp}(\hat{x}) = \text{supp}(x)$, if certain requirements are satisfied with the coherence parameter μ (Th.5.1 in [28], Th.4 in [31] or Th.3.1 in [32]) or Restricted Isometry Property (RIP) (Th.2 in [25]).

Existing results have mainly focused on the measurement perturbation, yet researches concerning the general perturbations are relatively rare. Here, the general perturbations involve a perturbed sensing matrix as well as a perturbed measurement vector. Two scenarios are considered in this paper from different perspective of views, where the measurement perturbation b is both involved due to imperfect measuring such as quantization effects.

The first scenario is from user's perspective of view, which means the sensing matrix of the system is not accurately

Jie Ding, Laming Chen, and Yuantao Gu are with the Department of Electronic Engineering, Tsinghua University, Beijing, 100084, CHINA. E-mail: gyt@tsinghua.edu.cn.

This work was supported partially by the National Natural Science Foundation of CHINA (60872087 and U0835003) and Agilent Technologies Foundation # 2205.

known, or not known at all. Thus the sensing process is in the form of

$$\tilde{\mathbf{y}} = \Phi \mathbf{x} + \mathbf{b}, \quad \tilde{\Phi} = \Phi + \mathbf{E}, \quad (3)$$

with recovery process

$$(N_2) \quad \hat{\mathbf{x}} = R(\tilde{\mathbf{y}}, \tilde{\Phi}, \dots).$$

The system perturbation $\mathbf{E}$ is introduced because of mis-modeling of the system, or the error involved during system calibration. Since the available sensing matrix is the perturbed $\tilde{\Phi}$ instead of Φ , the condition for recovery is also in terms of the former.

The second scenario is from designer's perspective of view, which means the system perturbation $\mathbf{E}$ is introduced by physical implementation of a designed system model Φ [35]. Thus the sensing process is in the form of

$$\tilde{\mathbf{y}} = \tilde{\Phi} \mathbf{x} + \mathbf{b}, \quad \tilde{\Phi} = \Phi + \mathbf{E}, \quad (4)$$

with recovery process

$$(N'_2) \quad \hat{\mathbf{x}} = R(\tilde{\mathbf{y}}, \Phi, \dots).$$

Since the available sensing matrix is the ideal one, the condition for recovery should be in terms of Φ in this scenario.

Herman and Strohmer have studied the accuracy of BP solution in (N_2) process [36]. Later, Herman and Needell also gave the recovery error of CoSaMP [37]. However, as far as we know, few works have been done yet on the perfect support recovery or the recovery error of OMP under general perturbations.

Analysis of OMP considering general perturbations and support recovery may benefit the analysis of many other greedy algorithms. In some practical applications, recovering the support set other than a more accurate estimation is a fundamental concern [35], [38]. In this paper, a completely perturbed scenario in the form of (3) is considered and the performance of OMP in (N_2) process is studied. It is shown that under certain RIP based conditions, the locations of k largest magnitude entries of a almost sparse signal $\mathbf{x}$ can be exactly recovered via OMP. Furthermore, an upper bound on the recovery error is given. It is also demonstrated that the results generalize the previous study concerning OMP in (N_0) process in [23]–[25], [27]. The completely perturbed scenario (4) together with (N'_2) process is also discussed.

The rest of the paper is organized as follows. Section II gives a brief review of OMP and RIP, as well as certain necessary assumptions and notations. Section III presents the main theoretical results on the completely perturbed scenarios. Several extensions are also presented with respect to special signals. Section IV provides the proofs of the theorems. Section V discusses some related works. The whole paper is concluded in Section VI. To make the paper more readable, some proofs are relegated as an appendix in Section VII.

II. BACKGROUND

A. Orthogonal Matching Pursuit (OMP)

The key idea of OMP lies in the attempt to reconstruct the support set Λ of $\mathbf{x}$ iteratively by starting with $\Lambda = \emptyset$.

TABLE I
THE OMP ALGORITHM

Input:	$\mathbf{y}, \Phi;$
Initialization:	$\mathbf{r}^0 = \mathbf{y}, \Lambda^0 = \emptyset, l = 0;$
Repeat	
	$l = l + 1;$
	match step:
	$\mathbf{h}^l = \Phi^T \mathbf{r}^{l-1};$
	identify step:
	$\Lambda^l = \Lambda^{l-1} \cup \{\arg \max_j \mathbf{h}^l(j) \};$
	update step:
	$\mathbf{x}^l = \arg \min_{\mathbf{z}: \text{supp}(\mathbf{z}) \subseteq \Lambda^l} \ \mathbf{y} - \Phi \mathbf{z}\ _2;$
	$\mathbf{r}^l = \mathbf{y} - \Phi \mathbf{x}^l;$
Until	stop criterion satisfied;
Output:	$\mathbf{x}^k.$

In the l th iteration, the inner products between the columns of Φ and the residual $\mathbf{r}^{l-1}$ are calculated, and the index of the largest absolute value of inner products is added to Λ . Here, the residual $\mathbf{r}^{l-1}$ from the former iteration represents the component of the measurement vector $\mathbf{y}$ that cannot be spanned by the columns of Φ indexed by Λ . In this way, the columns of Φ which are “the most relative” to $\mathbf{y}$ are iteratively chosen. The OMP algorithm is described in Table I.

In fact, OMP can be well expressed using $\mathbf{y}, \Phi, \Lambda^l$, Moore-Penrose pseudoinverse, and orthogonal projection operator. A brief review of them is given as follows (see [23] for more details).

Let $\mathbf{u}_{|\Lambda}$ denote the $|\Lambda| \times 1$ vector containing the entries of $\mathbf{u}$ indexed by Λ . Define $\mathbf{u}(j)$ as the j th entry of vector $\mathbf{u}$. Let Φ_Λ denote the $m \times |\Lambda|$ matrix obtained by selecting the columns of sensing matrix Φ indexed by Λ . If Φ_Λ has full column rank, then $\Phi_\Lambda^\dagger = (\Phi_\Lambda^T \Phi_\Lambda)^{-1} \Phi_\Lambda^T$ is the Moore-Penrose pseudoinverse of Φ_Λ . Let $\mathbf{P}_\Lambda = \Phi_\Lambda \Phi_\Lambda^\dagger$ and $\mathbf{P}_\Lambda^\perp = \mathbf{I} - \mathbf{P}_\Lambda$ denote the orthogonal projection operator onto the column space of Φ_Λ and its orthogonal complement, respectively. Define $\mathbf{A}_\Lambda = \mathbf{P}_\Lambda^\perp \Phi$ and $\mathbf{A}_\Lambda = \Phi$ when $\Lambda = \emptyset$, then $\mathbf{A}_\Lambda$ has the same size as Φ . From the theory of linear algebra, any orthogonal projection operator $\mathbf{P}$ obeys $\mathbf{P} = \mathbf{P}^T = \mathbf{P}^2$ and the columns of $\mathbf{A}_\Lambda$ indexed by Λ are zeros.

In the l th iteration, we begin with the estimation Λ^{l-1} from the previous iteration. The discussion below demonstrates the generation of Λ^l .

In the update step of the previous iteration, which is actually solving a least square problem, one has

$$\mathbf{r}^{l-1} = \mathbf{y} - \Phi \mathbf{x}^{l-1} = \mathbf{y} - \Phi_{\Lambda^{l-1}} \Phi_{\Lambda^{l-1}}^\dagger \mathbf{y} = \mathbf{P}_{\Lambda^{l-1}}^\perp \mathbf{y}. \quad (5)$$

In the matching step, one has

$$\mathbf{h}^l = \Phi^T \mathbf{r}^{l-1} = \Phi^T (\mathbf{P}_{\Lambda^{l-1}}^\perp)^T \mathbf{P}_{\Lambda^{l-1}}^\perp \mathbf{y} = \mathbf{A}_{\Lambda^{l-1}}^T \mathbf{r}^{l-1}. \quad (6)$$

From (5), (6), and the fact that the columns of $\mathbf{A}_\Lambda$ indexed by Λ are zeros, it can be derived that

$$\mathbf{h}^l(j) = 0, \quad \forall j \in \Lambda^{l-1}. \quad (7)$$

Therefore $\arg \max_j |\mathbf{h}^l(j)| \notin \Lambda^{l-1}$, $|\Lambda^l| = l$.

It is important to notice that the above property still holds when $\mathbf{y}$ and Φ are replaced by the contaminated $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$. To

see this, it is calculated that

$$\mathbf{r}^{l-1} = \tilde{\mathbf{y}} - \tilde{\Phi} \mathbf{x}^{l-1} = \tilde{\mathbf{y}} - \tilde{\Phi}_{\Lambda^{l-1}} \tilde{\Phi}_{\Lambda^{l-1}}^\dagger \tilde{\mathbf{y}} = \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \tilde{\mathbf{y}}, \quad (8)$$

$$\mathbf{h}^l = \tilde{\Phi}^\top \mathbf{r}^{l-1} = \tilde{\Phi}^\top (\tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp)^\top \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \tilde{\mathbf{y}} = \tilde{\mathbf{A}}_{\Lambda^{l-1}}^\top \mathbf{r}^{l-1}, \quad (9)$$

where $\tilde{\mathbf{P}}_{\Lambda}^\perp$ and $\tilde{\mathbf{A}}_{\Lambda}$ are defined by the perturbed sensing matrix $\tilde{\Phi}$. Due to the fact that the columns of $\tilde{\mathbf{A}}_{\Lambda^{l-1}}$ indexed by Λ^{l-1} still equal zeros, (7) holds in the completely perturbed scenario.

B. The Restricted Isometry Property (RIP)

For each integer $k = 1, 2, \dots, n$, the RIP for any matrix $\mathbf{A} \in \mathbb{C}^{m \times n}$ defines the restricted isometry constant (RIC) δ_k as the smallest nonnegative number such that

$$(1 - \delta_k) \|\mathbf{x}\|_2^2 \leq \|\mathbf{A}\mathbf{x}\|_2^2 \leq (1 + \delta_k) \|\mathbf{x}\|_2^2 \quad (10)$$

holds for any k -sparse vector $\mathbf{x}$ [39]. It is easy to check that if $\mathbf{A}$ satisfies the RIP of order k_1 and k_2 with isometry constants δ_{k_1} and δ_{k_2} , respectively, and $k_1 \leq k_2$, then one has $\delta_{k_1} \leq \delta_{k_2}$.

Since its introduction, the RIP has been widely used as a tool to guarantee successful sparse recovery for various algorithms. For example, for the (N_0) process, the RIP of order $2k$ with $\delta_{2k} < 0.03/\sqrt{\log k}$ guarantees exact recovery for any k -sparse signal via ROMP algorithm [15]; the RIP of order $3k$ with $\delta_{3k} < 0.165$ permits SP algorithm to exactly recover any k -sparse signal [17].

However, analyzing the performance of OMP with RIP was relatively elusive before Davenport and Wakin's work in [23]. They demonstrated that RIP can be used for a very straightforward analysis of OMP in (N_0) process. It is shown that if $\mathbf{y} = \Phi \mathbf{x}$ and $\mathbf{x}$ is a k -sparse signal, then $\delta_{k+1} < 1/(3\sqrt{k})$ is sufficient for exact recovery of OMP [23] (Th.3.1). Later, Liu and Temlyakov relaxed the bound to $1/((1 + \sqrt{2})\sqrt{k})$ [24] (Th.5.2). Huang and Zhu further changed the bound to $1/(1 + 2\sqrt{k})$, and they also discussed the performance for the (N_1) process [25]. In [27], it has been proved that $1/(1 + \sqrt{k})$ is sufficient for (N_0) process, while for any given $k > 1$, there exists a sensing matrix with $\delta_{k+1} = 1/\sqrt{k}$ and a k -sparse signal that exact recovery via OMP is not guaranteed. Therefore, if one uses the RIP of order $k + 1$ as a sufficient condition for exact recovery of a sparse signal via OMP, little improvement is possible. In terms of the number of measurements, it was demonstrated in [23] that $\delta_{k+1} < 1/(1 + \sqrt{k})$ requires $O(k^2 \log(n/k))$ measurements, and the number is roughly the same as what is required by coherence-based analysis in [21].

C. Assumptions and Notations

A vector $\mathbf{x} \in \mathbb{C}^n$ is k -sparse if it contains no more than k nonzero entries. Throughout this paper, however, the signal to be recovered is not limited to a sparse one. For a non-sparse signal $\mathbf{x}$, define the 'head' $\mathbf{x}^{(1)} \in \mathbb{C}^n$ as the k -sparse signal that contains the k largest magnitude entries of $\mathbf{x}$, i.e. the best k -sparse approximation of $\mathbf{x}$, and define the 'tail' $\mathbf{x}^{(2)} = \mathbf{x} - \mathbf{x}^{(1)}$. In order to delineate the compressibility of a general signal $\mathbf{x}$, define

$$\beta = \frac{\|\mathbf{x}^{(2)}\|_2}{\|\mathbf{x}^{(1)}\|_2}, \quad \gamma = \frac{\|\mathbf{x}^{(2)}\|_1}{\sqrt{k}\|\mathbf{x}^{(1)}\|_2}.$$

In this paper, $\mathbf{x}$ is assumed to be almost sparse, i.e. β and γ are far less than 1. When $\mathbf{x}^{(2)} = \mathbf{0}$, one has $\beta = \gamma = 0$, and $\mathbf{x}$ reduces to a sparse signal.

The notation of strong-decaying sparse signals is introduced by Davenport and Wakin in [23]. In our work, such concept is extended to general signals termed strong-decaying signals. Let $\{\mathbf{x}(m_j)\}_{1 \leq j \leq n}$ denote the entries of $\mathbf{x}$ rearranged in descending order by magnitude. $\mathbf{x}$ is called an α -strong-decaying signal if for all $j \in \{1, 2, \dots, n-1\}$ and $\mathbf{x}(m_{j+1}) \neq 0$, $|\mathbf{x}(m_j)|/|\mathbf{x}(m_{j+1})| \geq \alpha$, where $\alpha > 1$ is a constant.

When (N_2) or (N'_2) process is concerned, it is necessary to consider the nature of $\mathbf{b}$ and $\mathbf{E}$, and how they influence the process of OMP. This leads to the following definitions of relative bounds, which were introduced by Herman and Strohmer in [36].

The symbols $\|\cdot\|_2$ and $\|\cdot\|_2^{(k)}$ denote the spectral norm of a matrix and the largest spectral norm taken over all k -column submatrices, respectively. The perturbations $\mathbf{b}$ and $\mathbf{E}$ can be quantified as

$$\frac{\|\mathbf{b}\|_2}{\|\Phi \mathbf{x}\|_2} \leq \varepsilon_b, \quad \frac{\|\mathbf{E}\|_2^{(k)}}{\|\Phi\|_2^{(k)}} \leq \varepsilon, \quad (11)$$

where $\|\Phi \mathbf{x}\|_2$, $\|\Phi\|_2$, and $\|\Phi\|_2^{(l)}$ are nonzero. These relative upper bounds provide an access to analyze the influence of $\mathbf{b}$ and $\mathbf{E}$, even though the exact forms of them are unknown. Throughout this paper, it is appropriate to assume that ε_b and ε are far less than 1.

III. CONTRIBUTIONS

In this section, a completely perturbed scenario in the form of (3) is considered and the performance of OMP in (N_2) process is studied. Theorem 1 presents the RIP-based condition under which the support set of the head of $\mathbf{x}$ can be exactly recovered. In Theorem 2, we construct a sensing matrix and perturbations with which an almost sparse signal cannot be recovered. The RIC of the matrix is slightly bigger than that in the condition of Theorem 1, which indicates that the sufficient condition in Theorem 1 is rather tight. Several extensions with respect to special signals such as strong-decaying signals are put forward in Theorem 3 and 4. In Theorem 5, perturbations in the form of (4) is considered and the performance of OMP in (N'_2) process is studied. The following theorems and remarks summarize the main results.

Theorem 1: Suppose that the inputs $\mathbf{y}$ and Φ of OMP algorithm are contaminated by noise in the form of (3), and that the original signal $\mathbf{x}$ is almost sparse. Define the relative perturbations ε_b and ε as in (11). Let $t_0 = \min_{j \in \text{supp}(\mathbf{x}^{(1)})} |\mathbf{x}(j)|$, and

$$\varepsilon_h = \frac{1.23}{1 - \varepsilon} (\varepsilon + \varepsilon_b + (1 + \varepsilon_b)(\beta + \gamma)) \|\mathbf{x}^{(1)}\|_2. \quad (12)$$

If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\tilde{\delta}_{k+1} < Q(k, \varepsilon_h/t_0), \quad (13)$$

then OMP will recover the support set of $\mathbf{x}^{(1)}$ exactly from $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$ in k iterations, and the error between $\mathbf{x}^{(1)}$ and the

recovered k -sparse signal $\hat{x}$ can be bounded as

$$\|\hat{x} - x^{(1)}\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \delta_k}}. \quad (14)$$

In (13) the function $Q(\cdot, \cdot)$ is defined as

$$Q(u, v) = \frac{1}{\sqrt{u} + 1} - \frac{3}{\sqrt{u} + 1}v. \quad (15)$$

Proof: The proof is postponed to Section IV-B. ■

Remark 1: Theorem 1 reveals that if the RIC of the available sensing matrix $\tilde{\Phi}$ is known to be under a threshold, it is guaranteed that the support set of the head of a signal can be recovered.

It is of great significance to properly interpret ε_h/t_0 in (13). On one hand, the effects of $\mathbf{b}$ and $\mathbf{E}$ are reflected in terms of the worst-case relative perturbation ε_b and ε , respectively. Therefore, ε_h represents a worst-case effect from perturbed $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$. If more information on $\mathbf{b}$ and $\mathbf{E}$ is known, it may be possible to estimate a smaller ε_h . On the other hand, t_0 is the smallest magnitude of nonzero entries in $x^{(1)}$ and represents the capability of a sparse signal to be recovered against perturbations. Therefore, t_0/ε_h has a natural interpretation as a lower bound on the minimum component SNR. One can see that the larger t_0/ε_h is, the weaker the requirement of $\tilde{\delta}_{k+1}$ needs.

Remark 2: Considering (N_0) process, Theorem 1 generalizes the results in [23]–[25], [27]. If vector $\mathbf{y}$ and matrix Φ are unperturbed, and $\mathbf{x}$ is k -sparse, then (13) reduces to

$$\delta_{k+1} < \frac{1}{\sqrt{k} + 1}, \quad (16)$$

which is exactly the result in [27].

Remark 3: It needs to be pointed out that in order to be well defined, $Q(k, \varepsilon_h/t_0)$ should be greater than zero. Thus one gets

$$t_0 > 3\varepsilon_h. \quad (17)$$

It means that for the head of an almost sparse signal, the lower bound on the minimum component SNR should be large enough, so that its support can be extracted despite various noises.

When $\mathbf{x}$ is k -sparse and only the measurement vector $\mathbf{y}$ is perturbed, two corollaries can be derived from Theorem 1.

Corollary 1: Suppose that $\mathbf{E} = \mathbf{0}$ in (3) and that the original signal $\mathbf{x}$ is k -sparse. Let

$$\varepsilon_h = 1.23\varepsilon_b\|\mathbf{x}\|_2.$$

If Φ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < Q(k, \varepsilon_h/t_0), \quad (18)$$

then OMP will recover the support set of $\mathbf{x}$ exactly from $\tilde{\mathbf{y}}$ and Φ in k iterations, and the error between $\mathbf{x}$ and the recovered k -sparse signal $\hat{x}$ can be bounded as

$$\|\hat{x} - x\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \delta_k}}. \quad (19)$$

Corollary 1': Suppose that $\mathbf{E} = \mathbf{0}$ in (3) and that the original signal $\mathbf{x}$ is k -sparse. If Φ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < \frac{1 - \mu}{\sqrt{k} + 1}, \quad (20)$$

where $\mu \in (0, 1)$ is a constant, and

$$\|\mathbf{b}\|_2 \leq \mu t_0/3, \quad (21)$$

then OMP will recover the support set of $\mathbf{x}$ exactly from $\tilde{\mathbf{y}}$ and Φ in k iterations, and the error between $\mathbf{x}$ and the recovered k -sparse signal $\hat{x}$ can be bounded as

$$\|\hat{x} - x\|_2 \leq \frac{\|\mathbf{b}\|_2}{\sqrt{1 - \delta_k}}. \quad (22)$$

Remark 4: Both Corollary 1 and Corollary 1' concerns the condition for exact recovery of $\text{supp}(\mathbf{x})$ under measurement perturbation, but they are obtained from different point of views. In Corollary 1', the bound of δ_{k+1} is a constant, while the ℓ_2 norm of measurement perturbation should be under a threshold. A comparison of Corollary 1' with a similar conclusion [25] (Th.2) will be given in Section V.

When neither the measurement vector nor the sensing matrix is perturbed, the following corollary gives a sufficient condition under which the support of the head of an almost sparse signal can be exactly recovered.

Corollary 2: Suppose that $\mathbf{b} = \mathbf{0}$, $\mathbf{E} = \mathbf{0}$ in (3), and that the original signal $\mathbf{x}$ is almost sparse. Let

$$\varepsilon_h = 1.23(\beta + \gamma)\|\mathbf{x}^{(1)}\|_2. \quad (23)$$

If Φ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < Q(k, \varepsilon_h/t_0), \quad (24)$$

then OMP will recover the support set of $\mathbf{x}^{(1)}$ exactly from $\mathbf{y}$ and Φ in k iterations, and the error between $\mathbf{x}^{(1)}$ and the recovered k -sparse signal $\hat{x}$ can be bounded as

$$\|\hat{x} - x^{(1)}\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \delta_k}}. \quad (25)$$

Inspired by the work [27], the following theorem reveals how tight the RIP-based condition in Theorem 1 is.

Theorem 2: Consider the completely perturbed scenario (3). For any given positive integer $k \geq 2$, constants $t_0 > 0$ and $0 \leq e < t_0$, there exist an almost sparse signal $\mathbf{x} \in \mathbb{C}^{k+1}$, a sensing matrix $\Phi \in \mathbb{C}^{(k+1) \times (k+1)}$, perturbations $\mathbf{E}$ and $\mathbf{b}$ such that the smallest nonzero magnitude of k -sparse head $\mathbf{x}^{(1)}$ is t_0 ,

$$e = \|\mathbf{e}\|_2 = \|\tilde{\Phi}\mathbf{x}^{(2)} - \mathbf{E}\mathbf{x} + \mathbf{b}\|_2,$$

and the perturbed sensing matrix $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\tilde{\delta}_{k+1} \leq \frac{1}{\sqrt{k}} - \frac{\sqrt{k-1}}{k} \frac{e}{t_0}. \quad (26)$$

Furthermore, OMP fails to recover the support set of $\mathbf{x}^{(1)}$ from $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$ in k iterations.

Proof: The proof is postponed to Section IV-C. ■

Compared with Theorem 3.2 in [27], Theorem 2 takes general perturbation as well as non-sparseness of $\mathbf{x}$ into

consideration. Setting $e = 0$ in Theorem 2, it reduces to the result in [27], thus our work is a generalized version.

Remark 5: It will be shown that the bound (13) is rather tight. Recall that the proof of Theorem 1 is twofold. First, (35) is proved to be a sufficient condition for support recovery of $\mathbf{x}^{(1)}$. Second, $\|\mathbf{e}\|_2$ is estimated by $\|\mathbf{e}\|_2 \leq \varepsilon_h$. Correspondingly, we demonstrate that little improvement can be made on them. First, comparing (26) with (35), these two bounds are both linear decreasing function of e/t_0 , and as k tends to infinity, the ratio of their y -intercepts approaches 1 while the ratio of their slopes approaches 3. Second, as for the upper bound of $\|\mathbf{e}\|_2$, Proposition 3.5 in [16] and triangle inequality are used. For the sake of brevity, we assume that $\mathbf{x}$ is k -sparse and prove that

$$\|\mathbf{e}\|_2 = \frac{\sqrt{1 + \tilde{\delta}_k}}{1 - \varepsilon}(\varepsilon + \varepsilon_b)\|\mathbf{x}\|_2$$

can be satisfied. First, let $\mathbf{E} = -\varepsilon\tilde{\Phi}$, and choose a k -sparse signal $\mathbf{x}$ that satisfies $\|\tilde{\Phi}\mathbf{x}\|_2 = \sqrt{1 + \tilde{\delta}_k}\|\mathbf{x}\|_2$. Let $\mathbf{b} = \varepsilon_b\tilde{\Phi}\mathbf{x}$. Then it holds that

$$\begin{aligned} \|\mathbf{e}\|_2 &= \|\mathbf{E}\mathbf{x} + \mathbf{b}\|_2 = \|(\varepsilon + \varepsilon_b)\tilde{\Phi}\mathbf{x}\|_2 \\ &= (\varepsilon + \varepsilon_b)\frac{\|\tilde{\Phi}\mathbf{x}\|_2}{1 - \varepsilon} = \frac{\sqrt{1 + \tilde{\delta}_k}}{1 - \varepsilon}(\varepsilon + \varepsilon_b)\|\mathbf{x}\|_2. \end{aligned}$$

Due to the above two reasons, we show that the bound (13) in Theorem 1 is rather tight.

For α -strong-decaying signals, the requirement of isometry constant $\tilde{\delta}_{k+1}$ can be relaxed, and the locations can even be picked up in the order of their entries' magnitude as long as the decaying constant α is large enough. This is what the following two theorems reveal.

Theorem 3: Suppose that the inputs $\mathbf{y}$ and $\tilde{\Phi}$ of OMP algorithm are contaminated by noise as in (3), and that the original signal $\mathbf{x}$ is α -strong-decaying. Let

$$\varepsilon_h = \frac{1.23}{1 - \varepsilon}(\varepsilon + \varepsilon_b + (1 + \varepsilon_b)C\alpha^{-k})\|\mathbf{x}^{(1)}\|_2$$

and $k^* = (\sum_{i=0}^{k-1} \alpha^i)^2 / (\sum_{i=0}^{k-1} \alpha^{2i})$, where C is a constant depending only on α . If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\tilde{\delta}_{k+1} < Q(k^*, \varepsilon_h/t_0), \quad (27)$$

then OMP will recover the support set of $\mathbf{x}^{(1)}$ exactly from $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$ in k iterations, and the error between $\mathbf{x}^{(1)}$ and the recovered k -sparse signal $\hat{\mathbf{x}}$ can be bounded as

$$\|\hat{\mathbf{x}} - \mathbf{x}^{(1)}\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \tilde{\delta}_k}}. \quad (28)$$

Proof: The proof is postponed to Section IV-D. ■

Remark 6: Theorem 3 reveals that relaxed requirement of $\tilde{\delta}_{k+1}$ guarantees the recovery of a strong-decaying signal, and that the larger α is, the easier the requirement of $\tilde{\delta}_{k+1}$ can be satisfied. To see this, notice that for $k > 1$, Cauchy-Schwarz inequality implies $k^* < k$, and thus

$$Q(k, \varepsilon_h/t_0) < Q(k^*, \varepsilon_h/t_0).$$

Define $k^* = L(\alpha) = (\sum_{i=0}^{k-1} \alpha^i)^2 / \sum_{i=0}^{k-1} \alpha^{2i}$. Because $L(\alpha)$ is a decreasing function of α , the larger α is, the smaller k^* is, and the easier the requirement of $\tilde{\delta}_{k+1}$ can be satisfied.

Corollary 3: Suppose that the measurement vector and sensing matrix are unperturbed, and that the original signal $\mathbf{x}$ is a k -sparse α -strong-decaying one. If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < \frac{1}{\sqrt{k^* + 1}}, \quad (29)$$

then OMP will recover $\mathbf{x}$ exactly from $\mathbf{y}$ and $\tilde{\Phi}$ in k iterations.

Remark 7: Because $k^* < (\alpha + 1)/(\alpha - 1)$, (29) can be replaced by

$$\delta_{k+1} < \frac{1}{\sqrt{(\alpha + 1)/(\alpha - 1) + 1}}.$$

Furthermore, if α is far greater than 1, the requirement approximately reduces to $\delta_{k+1} < 0.5$, which is very interesting.

Theorem 4: Suppose that the inputs $\mathbf{y}$ and $\tilde{\Phi}$ of OMP algorithm are contaminated by noise as in (3), and that the original signal $\mathbf{x}$ is α -strong-decaying. Let

$$\varepsilon_h = \frac{1.23}{1 - \varepsilon}(\varepsilon + \varepsilon_b + (1 + \varepsilon_b)C\alpha^{-k})\|\mathbf{x}^{(1)}\|_2,$$

where C is a constant depending only on α . If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\tilde{\delta}_{k+1} < \frac{1}{3} - \frac{2\varepsilon_h}{3t_0},$$

and

$$\alpha \geq \max \left\{ G(\tilde{\delta}_{k+1}), 1.2 \right\} \quad (30)$$

where

$$G(u) = \frac{1 + u}{1 - 3u - \frac{2\varepsilon_h}{t_0}}, \quad (31)$$

then OMP will recover the support set of $\mathbf{x}^{(1)}$ exactly from $\tilde{\mathbf{y}}$ and $\tilde{\Phi}$ in k iterations, and the recovery is in the order of the signal entries' magnitude.

Proof: The proof is postponed to Section IV-E. ■

Remark 8: For (N_0) process with k -sparse signal $\mathbf{x}$, Davenport and Wakin proved that if $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with $\delta_{k+1} < 1/3$, and

$$\alpha > \frac{1 + \delta_{k+1}(2\sqrt{k-1} - 1)}{1 - 3\delta_{k+1}} \triangleq I(\delta_{k+1}), \quad (32)$$

then OMP will recover $\mathbf{x}$ sequentially from $\mathbf{y}$ and $\tilde{\Phi}$ in k iterations [23] (Th.4.1). When $\mathbf{x}$ is no longer sparse, and the sensing matrix as well as the measurement vector is perturbed, Theorem 4 shows that the elements of $\text{supp}(\mathbf{x})$ can still be picked up sequentially. Specially, the following Corollary 4 is derived.

Corollary 4: Suppose that $\mathbf{y}$ and $\tilde{\Phi}$ are unperturbed, and that the original signal $\mathbf{x}$ is a k -sparse α -strong-decaying one. If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < \frac{1}{3},$$

and

$$\alpha > \max \left\{ \frac{1 + \delta_{k+1}}{1 - 3\delta_{k+1}}, 1.2 \right\}, \quad (33)$$

then OMP will recover $\mathbf{x}$ exactly from $\mathbf{y}$ and Φ in k iterations, and the recovery is in the order of the entries' magnitude.

For $k > 1$, one has $2\sqrt{k-1} - 1 \geq 1$. Thus, it can be seen from (32) and (33) that Corollary 4 is better than the conclusion in [23] when $I(\delta_{k+1})$ is greater than 1.2.

At the end of the main contribution, perturbations in the form of (4) is considered.

Theorem 5: Suppose that the inputs $\mathbf{y}$ and Φ of OMP algorithm are contaminated by noise as in (4), and that the original signal $\mathbf{x}$ is almost sparse. Define the relative perturbations ε as that in (11), and ε_b as:

$$\frac{\|\mathbf{b}\|_2}{\|\Phi\mathbf{x}\|_2} \leq \varepsilon_b.$$

Let

$$\varepsilon_h = 1.23(\varepsilon + \varepsilon_b + \varepsilon\varepsilon_b + (1 + \varepsilon_b)(1 + \varepsilon)(\beta + \gamma))\|\mathbf{x}^{(1)}\|_2.$$

If Φ satisfies the RIP of order $k + 1$ with isometry constant

$$\delta_{k+1} < Q(k, \varepsilon_h/t_0),$$

then OMP will recover the support set of $\mathbf{x}^{(1)}$ exactly from $\tilde{\mathbf{y}}$ and Φ in k iterations, and the error between $\mathbf{x}^{(1)}$ and the recovered k -sparse signal $\hat{\mathbf{x}}$ can be bounded as

$$\|\hat{\mathbf{x}} - \mathbf{x}^{(1)}\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \delta_k}}.$$

Proof: The proof is postponed to Section IV-F. ■

Remark 9: The definition of ε_b in Theorem 5 is different from that in Theorem 1. This is due to the fact that ε_b denotes the relative measurement perturbation added to the output of the system, and the output in this scenario is $\tilde{\Phi}\mathbf{x}$ other than $\Phi\mathbf{x}$. By comparison of Theorem 1 and 5, it can be seen that their main difference comes from the respective definition of ε_b . Based on the completely perturbed scenario (4), several results similar to Theorem 2-4 can be derived without much difficulty. However, they are not included for conciseness.

IV. PROOFS

A. Lemmas

Before the proofs of the main theorems, two helpful lemmas are given first. Their proofs are postponed in Appendix.

Lemma 1: Let $\{x_i\}_{1 \leq i \leq l}$ denote l positive variables satisfying $x_i/x_{i-1} \geq \alpha$ for all i , where $\alpha > 1$ is a constant. Then the function $f(x_1, x_2, \dots, x_l) = (\sum_{i=1}^l x_i^2)/(\sum_{i=1}^l x_i)^2$ equals its minimum $(\sum_{i=0}^{l-1} \alpha^{2i})/(\sum_{i=0}^{l-1} \alpha^i)^2$ when $x_i/x_{i-1} = \alpha$, $i = 2, \dots, l$.

Lemma 2: Suppose that the inputs $\mathbf{y}$ and Φ of OMP algorithm are contaminated by noise as in (3), and that the original signal $\mathbf{x}$ is an α -strong-decaying one. Let

$$\varepsilon_h = \frac{1.23}{1 - \varepsilon}(\varepsilon + \varepsilon_b + (1 + \varepsilon_b)C\alpha^{-k})\|\mathbf{x}^{(1)}\|_2.$$

For the l th iteration, define $\mathbf{x}^* \in \mathbb{C}^n$ as the signal that contains the entries of $\mathbf{x}$ indexed by $\text{supp}(\mathbf{x}^{(1)}) \setminus \Lambda^{l-1}$ with the rest set

to zeros. If $\tilde{\Phi}$ satisfies the RIP of order $k + 1$ with isometry constant $\tilde{\delta}_{k+1}$, one has

$$|\mathbf{h}^l(j) - \mathbf{x}^*(j)| \leq \frac{\tilde{\delta}_{k+1}\|\mathbf{x}^*\|_2 + \varepsilon_h}{1 - \tilde{\delta}_{k+1}} \quad (34)$$

for all $j \notin \Lambda^{l-1}$.

B. Proof of Theorem 1

Proof: First of all, it will be proved that OMP exactly recovers the support set of $\mathbf{x}^{(1)}$ in k iterations. This proof consists of three parts. First, we prove that

$$\tilde{\delta}_{k+1} < \frac{1}{\sqrt{k} + 1} - \frac{3}{\sqrt{k} + 1} \frac{\|\mathbf{e}\|_2}{t_0} \quad (35)$$

implies

$$\tilde{\delta}_{k+1} < \frac{1}{\sqrt{k'} + 1} - \frac{\sqrt{k'} + 2}{\sqrt{k'} + 1} \frac{\|\mathbf{e}\|_2}{\sqrt{k'}t_0} \quad (36)$$

for all $1 \leq k' \leq k$. Second, define $\mathbf{e} = \tilde{\Phi}\mathbf{x}^{(2)} - \mathbf{E}\mathbf{x} + \mathbf{b}$. We prove that (36) is a sufficient condition for the support recovery in the l th iteration with $k' = k - l + 1$. At last, an upper bound of $\|\mathbf{e}\|_2$ is given.

First, define

$$c_1 = \frac{2 + \sqrt{k'}}{(1 + \sqrt{k'})\sqrt{k'}t_0}, \quad c_2 = \frac{2 + \sqrt{k'}}{(1 + \sqrt{k'})\sqrt{k'}t_0}, \quad (37)$$

then it's easy to check that $c_1 \leq c_2$. According to (35), it can be derived that

$$\begin{aligned} \tilde{\delta}_{k+1} &< \frac{1}{\sqrt{k} + 1} - c_1\|\mathbf{e}\|_2 \leq \frac{c_2}{c_1} \left(\frac{1}{\sqrt{k} + 1} - c_1\|\mathbf{e}\|_2 \right) \\ &= \frac{1}{\sqrt{k'} + 1} - \frac{\sqrt{k'} + 2}{\sqrt{k'} + 1} \frac{\|\mathbf{e}\|_2}{\sqrt{k'}t_0}, \end{aligned} \quad (38)$$

which implies (36).

The proof of the second part works by induction. To begin with, consider the first iteration where $\Lambda^0 = \emptyset$. (3) indicate that

$$\tilde{\mathbf{y}} = (\tilde{\Phi} - \mathbf{E})\mathbf{x} + \mathbf{b} = \tilde{\Phi}\mathbf{x}^{(1)} + \mathbf{e}. \quad (39)$$

Then,

$$\mathbf{h}^1 = \tilde{\Phi}^T \tilde{\mathbf{y}} = \tilde{\Phi}^T (\tilde{\Phi}\mathbf{x}^{(1)} + \mathbf{e}),$$

which can be rewritten as

$$\mathbf{h}^1(i) = \langle \tilde{\Phi}\mathbf{e}_i, \tilde{\Phi}\mathbf{x}^{(1)} + \mathbf{e} \rangle,$$

where $\langle \cdot, \cdot \rangle$ denotes the inner product in Euclidean space and $\mathbf{e}_i$ denotes the i th natural basis. Define

$$H = \max_{i \in \text{supp}(\mathbf{x}^{(1)})} |\mathbf{h}^1(i)|$$

and $U = \langle \tilde{\Phi}\mathbf{x}^{(1)}, \tilde{\Phi}\mathbf{x}^{(1)} + \mathbf{e} \rangle$. On one hand,

$$U = \sum \mathbf{x}^{(1)}(i)\mathbf{h}^1(i) \leq \|\mathbf{x}^{(1)}\|_1 H \leq \sqrt{k}\|\mathbf{x}^{(1)}\|_2 H. \quad (40)$$

On the other hand,

$$\begin{aligned} U &\geq \|\tilde{\Phi}\mathbf{x}^{(1)}\|_2^2 - \|\tilde{\Phi}\mathbf{x}^{(1)}\|_2 \|\mathbf{e}\|_2 \\ &\geq (1 - \tilde{\delta}_{k+1})\|\mathbf{x}^{(1)}\|_2^2 - \sqrt{1 + \tilde{\delta}_{k+1}}\|\mathbf{x}^{(1)}\|_2 \|\mathbf{e}\|_2. \end{aligned} \quad (41)$$

Thus one has

$$H \geq \frac{1}{\sqrt{k}}((1 - \tilde{\delta}_{k+1})\|\mathbf{x}^{(1)}\|_2 - \sqrt{1 + \tilde{\delta}_{k+1}}\|e\|_2). \quad (42)$$

For $i \notin \text{supp}(\mathbf{x}^{(1)})$, Lemma 2.1 in [30] implies that

$$\begin{aligned} |\mathbf{h}^1(i)| &= |\langle \tilde{\Phi} \mathbf{e}_i, \tilde{\Phi} \mathbf{x}^{(1)} \rangle + \langle \tilde{\Phi} \mathbf{e}_i, \mathbf{e} \rangle| \\ &\leq \tilde{\delta}_{k+1}\|\mathbf{x}^{(1)}\|_2 + \|\tilde{\Phi} \mathbf{e}_i\|_2\|e\|_2 \\ &\leq \tilde{\delta}_{k+1}\|\mathbf{x}^{(1)}\|_2 + \sqrt{1 + \tilde{\delta}_{k+1}}\|e\|_2. \end{aligned} \quad (43)$$

Because $\|\mathbf{x}^{(1)}\|_2 \geq \sqrt{k}t_0$, (36) of $k' = k$ together with (42) and (43) indicate that

$$H > |\mathbf{h}^1(i)|, \quad \forall i \notin \text{supp}(\mathbf{x}^{(1)}),$$

which guarantees the success of the first iteration.

Now consider the general induction step. In the l th iteration, suppose that all previous iterations succeed, which means that Λ^{l-1} is a subset of $\text{supp}(\mathbf{x}^{(1)})$. Define $\mathbf{z}^{l-1} = \mathbf{x}^{(1)} - \mathbf{x}^{l-1}$, then $\text{supp}(\mathbf{z}^{l-1}) \subsetneq \text{supp}(\mathbf{x}^{(1)})$. Because

$$\mathbf{h}^l = \tilde{\Phi}^T(\tilde{\mathbf{y}} - \tilde{\Phi} \mathbf{x}^{l-1}) = \tilde{\Phi}^T(\tilde{\Phi} \mathbf{x}^{(1)} - \tilde{\Phi} \mathbf{x}^{l-1} + \mathbf{e}),$$

one has

$$\mathbf{h}^l(i) = \langle \tilde{\Phi} \mathbf{e}_i, \tilde{\Phi} \mathbf{z}^{l-1} + \mathbf{e} \rangle.$$

Define

$$H = \max_{i \in \text{supp}(\mathbf{x}^{(1)})} |\mathbf{h}^l(i)|$$

and $U = \langle \tilde{\Phi} \mathbf{z}^{l-1}, \tilde{\Phi} \mathbf{z}^{l-1} + \mathbf{e} \rangle$. According to (7), it can be derived that

$$\begin{aligned} U &= \sum \mathbf{z}^{l-1}(i) \mathbf{h}^l(i) \leq \|\mathbf{z}^{l-1}\|_{\text{supp}(\mathbf{x}^{(1)}) \setminus \Lambda^{l-1}} \|H\|_1 \\ &\leq \sqrt{k-l+1} \|\mathbf{z}^{l-1}\|_2 H = \sqrt{k'} \|\mathbf{z}^{l-1}\|_2 H. \end{aligned} \quad (44)$$

Following the steps in the proof for the first iteration, and noticing that $\|\mathbf{z}^{l-1}\|_2 \geq \sqrt{k'}t_0$, it can be derived from (36) that

$$H > |\mathbf{h}^l(i)|, \quad \forall i \notin \text{supp}(\mathbf{x}^{(1)}).$$

According to (7), $\mathbf{h}^l(i) = 0$ for $i \in \Lambda^{l-1}$, which guarantees the success of the l th iteration. The proof of induction is completed.

Thirdly, an upper bound of $\|e\|_2$ is given as follows. According to Proposition 3.5 in [16],

$$\begin{aligned} \|\tilde{\Phi} \mathbf{x}^{(2)}\|_2 &\leq \sqrt{1 + \tilde{\delta}_k}(\|\mathbf{x}^{(2)}\|_2 + \frac{\|\mathbf{x}^{(2)}\|_1}{\sqrt{k}}) \\ &= \sqrt{1 + \tilde{\delta}_k}(\beta + \gamma)\|\mathbf{x}^{(1)}\|_2, \end{aligned}$$

and

$$\begin{aligned} \|\mathbf{E} \mathbf{x}\|_2 &\leq \|\mathbf{E} \mathbf{x}^{(1)}\|_2 + \|\mathbf{E} \mathbf{x}^{(2)}\|_2 \\ &\leq \|\mathbf{E}\|_2^{(k)}(\|\mathbf{x}^{(1)}\|_2 + \|\mathbf{x}^{(2)}\|_2 + \frac{\|\mathbf{x}^{(2)}\|_1}{\sqrt{k}}) \\ &\leq \frac{\varepsilon}{1 - \varepsilon} \sqrt{1 + \tilde{\delta}_k}(1 + \beta + \gamma)\|\mathbf{x}^{(1)}\|_2. \end{aligned}$$

Therefore,

$$\begin{aligned} \|e\|_2 &\leq \|\tilde{\Phi} \mathbf{x}^{(2)}\|_2 + \|\mathbf{E} \mathbf{x}\|_2 + \|\mathbf{b}\|_2 \\ &\leq \|\tilde{\Phi} \mathbf{x}^{(2)}\|_2 + \|\mathbf{E} \mathbf{x}\|_2 + \varepsilon_b \|\tilde{\Phi} \mathbf{x}\|_2 \\ &\leq (\|\tilde{\Phi} \mathbf{x}^{(2)}\|_2 + \|\mathbf{E} \mathbf{x}\|_2)(1 + \varepsilon_b) + \varepsilon_b \|\tilde{\Phi} \mathbf{x}^{(1)}\|_2 \\ &\leq \frac{\sqrt{1 + \tilde{\delta}_k}}{1 - \varepsilon}(\varepsilon + \varepsilon_b + (1 + \varepsilon_b)(\beta + \gamma))\|\mathbf{x}^{(1)}\|_2. \end{aligned} \quad (45)$$

Noticing that $\tilde{\delta}_k \leq 1/(\sqrt{k} + 1) \leq 0.5$, one has $\|e\|_2 \leq \varepsilon_h$. Therefore (13) implies (35), which guarantees the exact recovery of $\text{supp}(\mathbf{x}^{(1)})$.

To finish the proof, the recovery error is bounded as follows. Because $\Lambda = \text{supp}(\mathbf{x}^{(1)})$ is exactly recovered, one has

$$\hat{\mathbf{x}}|_{\Lambda} = \tilde{\Phi}_{\Lambda}^{\dagger} \tilde{\mathbf{y}} = \tilde{\Phi}_{\Lambda}^{\dagger}(\tilde{\Phi}_{\Lambda} \mathbf{x}^{(1)}|_{\Lambda} + \mathbf{e}) = \mathbf{x}^{(1)}|_{\Lambda} + \tilde{\Phi}_{\Lambda}^{\dagger} \mathbf{e}. \quad (46)$$

Thus

$$\|\hat{\mathbf{x}} - \mathbf{x}^{(1)}\|_2 \leq \|\tilde{\Phi}_{\Lambda}^{\dagger}\|_2 \|e\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \tilde{\delta}_k}}.$$

■

C. Proof of Theorem 2

Proof: First, we prove that there exist a k -sparse signal $\mathbf{x}^{(1)}$ with t_0 as its smallest nonzero entries' magnitude, a vector $\mathbf{e} \in \mathbb{C}^{k+1}$ satisfying $\|e\|_2 = e$, and a perturbed sensing matrix $\tilde{\Phi}$ with

$$\tilde{\delta}_{k+1} \leq \frac{1}{\sqrt{k}} - \frac{\sqrt{k-1}}{k} \frac{e}{t_0} \quad (47)$$

such that OMP fails to recover the support set of $\mathbf{x}^{(1)}$ from $\tilde{\Phi}$ and $\tilde{\mathbf{y}} = \tilde{\Phi} \mathbf{x}^{(1)} + \mathbf{e}$ in k iterations. Let

$$\tilde{\Phi} = \begin{pmatrix} \mathbf{I}_{k \times k} & a \mathbf{1}_{k \times 1} \\ \mathbf{0}_{1 \times k} & b \end{pmatrix}, \quad (48)$$

where $a = \delta/\sqrt{k}$ and $b = \sqrt{1 - \delta^2}$ are two constants with $\delta < 1/\sqrt{k}$. Since

$$\tilde{\Phi}^T \tilde{\Phi} = \begin{pmatrix} \mathbf{I}_{k \times k} & a \mathbf{1}_{k \times 1} \\ a \mathbf{1}_{1 \times k} & a^2 k + b^2 \end{pmatrix}, \quad (49)$$

it can be derived that the eigenvalues $\{\lambda_i\}_{i=1}^{k+1}$ of $\tilde{\Phi}^T \tilde{\Phi}$ are

$$\lambda_i = 1, \quad 1 \leq i \leq k-1, \quad \lambda_k = 1 - \delta, \quad \lambda_{k+1} = 1 + \delta. \quad (50)$$

Thus for $\tilde{\Phi}$, its RIC of order $k+1$ satisfies

$$\tilde{\delta}_{k+1} = \delta. \quad (51)$$

Let $\mathbf{x}^{(1)} = (t_0 \mathbf{1}_{1 \times k}, 0)^T$ and $\mathbf{e} = (\mathbf{0}_{1 \times k}, e)^T$, then the perturbed measurement vector

$$\tilde{\mathbf{y}} = \tilde{\Phi} \mathbf{x}^{(1)} + \mathbf{e} = (t_0 \mathbf{1}_{1 \times k}, e)^T.$$

Set

$$\delta = \frac{\sqrt{k} - (e/t_0)\sqrt{k-1} + (e/t_0)^2}{k + (e/t_0)^2},$$

then the matching vector $\mathbf{h}^1 = t_0 \mathbf{1}_{(k+1) \times 1}$, which implies that OMP fails in the first iteration. It is easy to check that

$$\delta \leq \frac{1}{\sqrt{k}} - \frac{\sqrt{k-1}}{k} \frac{e}{t_0}.$$

Second, let $\Phi = \mathbf{I}_{(k+1) \times (k+1)}$, $\mathbf{x}^{(2)} = (\mathbf{0}_{1 \times k}, e/2)^T$, $\mathbf{b} = (\mathbf{0}_{1 \times k}, e/2)^T$, then

$$\mathbf{E} = \begin{pmatrix} \mathbf{0}_{k \times k} & a\mathbf{1}_{k \times 1} \\ \mathbf{0}_{1 \times k} & b - 1 \end{pmatrix},$$

and $\mathbf{e} = \tilde{\Phi}\mathbf{x}^{(2)} - \mathbf{E}\mathbf{x} + \mathbf{b}$, which completes the proof of Theorem 2. ■

D. Proof of Theorem 3

Proof: The proof of Theorem 3 is similar to that of Theorem 1. For the sake of brevity, some revisions are made based on the proof of Theorem 1.

First, define

$$k'^* = \left(\sum_{i=0}^{k'-1} \alpha^i \right)^2 / \left(\sum_{i=0}^{k'-1} \alpha^{2i} \right).$$

According to Lemma 1, for any α -strong-decaying and k' -sparse signal $\mathbf{u}$, it holds that $\|\mathbf{u}\|_1 \leq \sqrt{k'^*} \|\mathbf{u}\|_2$. Therefore, (40) and (44) can be replaced by

$$U \leq \|\mathbf{x}^{(1)}\|_1 H \leq \|\mathbf{x}^{(1)}\|_2 \sqrt{k'^*} H$$

and

$$\begin{aligned} U &\leq \|\mathbf{z}^{l-1}\|_{\text{supp}(\mathbf{x}^{(1)}) \setminus \Lambda^{l-1}} H = \|\mathbf{x}^{(1)}\|_{\text{supp}(\mathbf{x}^{(1)}) \setminus \Lambda^{l-1}} H \\ &\leq \sqrt{k'^*} \|\mathbf{x}^{(1)}\|_{\text{supp}(\mathbf{x}^{(1)}) \setminus \Lambda^{l-1}} H \leq \sqrt{k'^*} \|\mathbf{z}^{l-1}\|_2 H \end{aligned}$$

respectively. Further, since

$$\|\mathbf{z}^{l-1}\|_2 \geq \left(\sum_{i=0}^{k'-1} \alpha^{2i} \right)^{1/2} t_0 \geq \sqrt{k'^*} t_0,$$

equation (36) can be replaced by

$$\tilde{\delta}_{k+1} < \frac{1}{\sqrt{k'^*} + 1} - \frac{\sqrt{k'^*} + 2}{\sqrt{k'^*} + 1} \frac{\|\mathbf{e}\|_2}{\sqrt{k'^*} t_0}. \quad (52)$$

Since $1 \leq k'^* \leq k^*$, (52) can be inferred by

$$\tilde{\delta}_{k+1} < \frac{1}{\sqrt{k^*} + 1} - \frac{3}{\sqrt{k^*} + 1} \frac{\|\mathbf{e}\|_2}{t_0}. \quad (53)$$

Second, an upper bound of $\beta + \gamma$ can be given in terms of α as follows

$$\begin{aligned} \beta + \gamma &\leq \frac{|\mathbf{x}(m_{k+1})| \left(\left(\sum_{i=0}^{\infty} \alpha^{-2i} \right)^{1/2} + \sum_{i=0}^{\infty} \alpha^{-i} / \sqrt{k} \right)}{|\mathbf{x}(m_{k+1})| \sqrt{\sum_{i=1}^k \alpha^{2i}}} \\ &= \frac{(1 - \alpha^{-2})^{-1/2} + (\sqrt{k}(1 - \alpha^{-1}))^{-1}}{\alpha(\alpha^{2k} - 1)^{1/2}(\alpha^2 - 1)^{-1/2}} \\ &= (1 + \frac{1}{\sqrt{k}} \sqrt{\frac{\alpha+1}{\alpha-1}})(\alpha^{2k} - 1)^{-1/2} \\ &\leq C\alpha^{-k}, \end{aligned}$$

where C is a constant only related to α . Therefore,

$$\begin{aligned} \|\mathbf{e}\|_2 &\leq \frac{\sqrt{1 + \tilde{\delta}_k}}{1 - \varepsilon} (\varepsilon + \varepsilon_b + (1 + \varepsilon_b)(\beta + \gamma)) \|\mathbf{x}^{(1)}\|_2 \\ &\leq \frac{\sqrt{1 + \tilde{\delta}_k}}{1 - \varepsilon} (\varepsilon + \varepsilon_b + (1 + \varepsilon_b)C\alpha^{-k}) \|\mathbf{x}^{(1)}\|_2. \end{aligned}$$

Notice that $\tilde{\delta}_k \leq 1/(\sqrt{k^*} + 1) \leq 0.5$, therefore (27) guarantees exact recovery of $\text{supp}(\mathbf{x}^{(1)})$. ■

E. Proof of Theorem 4

Proof: By induction it will be shown that (30) guarantees the order of recovery. For the l th iteration, suppose that all the locations recovered in the previous iterations are in order. Define $\mathbf{x}^*$ as that in Lemma 2. It will be demonstrated that OMP will choose the largest entry of $\mathbf{x}^*$, i.e. $\mathbf{x}(m_l)$. According to Lemma 2,

$$|\mathbf{h}^l(j) - \mathbf{x}^*(j)| \leq \frac{\tilde{\delta}_{k+1} \|\mathbf{x}^*\|_2 + \varepsilon_h}{1 - \tilde{\delta}_{k+1}}. \quad (54)$$

It can be calculated from $\alpha \geq 1.2$ that

$$\sqrt{\frac{1}{1 - \alpha^{-2}}} < 1 + \frac{1}{\alpha}.$$

Thus,

$$\|\mathbf{x}^*\|_2 < |\mathbf{x}(m_l)| \left(\sum_{i=0}^{\infty} \alpha^{-2i} \right)^{1/2} < |\mathbf{x}(m_l)| \left(1 + \frac{1}{\alpha} \right). \quad (55)$$

Combining (54) and (55), one has

$$\begin{aligned} |\mathbf{h}^l(m_l)| &> |\mathbf{x}(m_l)| - \Delta, \\ |\mathbf{h}^l(m_j)| &< |\mathbf{x}(m_{l+1})| + \Delta \leq |\mathbf{x}(m_l)| / \alpha + \Delta, \\ j &\in \{l+1, l+2, \dots, n\}, \end{aligned}$$

where

$$\Delta = \frac{1}{1 - \tilde{\delta}_{k+1}} (\tilde{\delta}_{k+1} |\mathbf{x}(m_l)| (1 + \frac{1}{\alpha}) + \varepsilon_h).$$

It is easy to check that $|\mathbf{h}^l(m_l)|$ is greater than $|\mathbf{h}^l(m_j)|$ for $j \in \{l+1, l+2, \dots, n\}$, if (30) is satisfied. ■

F. Proof of Theorem 5

Proof: For the sake of brevity, we only need to make some revisions based on the proof of Theorem 1. Noticing that the inputs are Φ and $\tilde{\mathbf{y}} = \tilde{\Phi}\mathbf{x} + \mathbf{b} = \Phi\mathbf{x}^{(1)} + \Phi\mathbf{x}^{(2)} + \mathbf{E}\mathbf{x} + \mathbf{b}$, $\tilde{\delta}_{k+1}$ and $\mathbf{e}$ in the proof of Theorem 1 need to be replaced by δ_{k+1} and $\Phi\mathbf{x}^{(2)} + \mathbf{E}\mathbf{x} + \mathbf{b}$.

Define $\mathbf{e} = \Phi\mathbf{x}^{(2)} + \mathbf{E}\mathbf{x} + \mathbf{b}$. An upper bound of $\|\mathbf{e}\|_2$ is given as follows. According to Proposition 3.5 in [16],

$$\begin{aligned} \|\Phi\mathbf{x}^{(2)}\|_2 &\leq \sqrt{1 + \delta_k} (\|\mathbf{x}^{(2)}\|_2 + \frac{\|\mathbf{x}^{(2)}\|_1}{\sqrt{k}}) \\ &= \sqrt{1 + \delta_k} (\beta + \gamma) \|\mathbf{x}^{(1)}\|_2, \end{aligned}$$

and

$$\begin{aligned} \|\mathbf{E}\mathbf{x}\|_2 &\leq \|\mathbf{E}\mathbf{x}^{(1)}\|_2 + \|\mathbf{E}\mathbf{x}^{(2)}\|_2 \\ &\leq \|\mathbf{E}\|_2^{(k)} (\|\mathbf{x}^{(1)}\|_2 + \|\mathbf{x}^{(2)}\|_2 + \frac{\|\mathbf{x}^{(2)}\|_1}{\sqrt{k}}) \\ &= \varepsilon \sqrt{1 + \delta_k} (1 + \beta + \gamma) \|\mathbf{x}^{(1)}\|_2. \end{aligned}$$

Therefore,

$$\begin{aligned} \|\mathbf{e}\|_2 &\leq \|\Phi\mathbf{x}^{(2)}\|_2 + \|\mathbf{E}\mathbf{x}\|_2 + \|\mathbf{b}\|_2 \\ &\leq \|\Phi\mathbf{x}^{(2)}\|_2 + \|\mathbf{E}\mathbf{x}\|_2 + \varepsilon_b \|\Phi\mathbf{x}\|_2 \\ &\leq (\|\Phi\mathbf{x}^{(2)}\|_2 + \|\mathbf{E}\mathbf{x}\|_2) (1 + \varepsilon_b) + \varepsilon_b \|\Phi\mathbf{x}^{(1)}\|_2 \\ &\leq \varepsilon_h, \end{aligned}$$

and

$$\|\hat{\mathbf{x}} - \mathbf{x}^{(1)}\|_2 \leq \|\Phi_\Lambda^\dagger\|_2 \|e\|_2 \leq \frac{\varepsilon_h}{\sqrt{1 - \delta_k}}.$$

■

V. RELATED WORKS

In this section, Theorem 2 in [25] and Theorem 3.1 in [40] are compared with Corollary 1' and Corollary 2 in this work, respectively.

In [25], it is proved that for (N_1) process, the support of a k -sparse signal $\mathbf{x}$ can be recovered, provided that

$$\delta_{k+1} < 1/(1 + (\sqrt{6} + 2)\sqrt{k})$$

and $\|\mathbf{b}\|_2 \leq \delta_k \sqrt{k} t_0$. By a comprehensive comparison, it is shown that this conclusion is not better than Corollary 1'.

First, let μ satisfy $1/(1 + (\sqrt{6} + 2)\sqrt{k}) = (1 - \mu)/(\sqrt{k} + 1)$, i.e.,

$$\mu = \frac{(\sqrt{6} + 1)\sqrt{k}}{1 + (\sqrt{6} + 2)\sqrt{k}}.$$

Consider the ratio of the required upperbound of $\|\mathbf{b}\|_2$ in the result in [25] to that in Corollary 1':

$$r = \frac{\delta_k \sqrt{k} t_0}{\mu t_0 / 3} = \frac{3}{\sqrt{6} + 1} (1 + (\sqrt{6} + 2)\sqrt{k}) \delta_k.$$

It can be concluded from $\delta_k \leq \delta_{k+1} < 1/(1 + (\sqrt{6} + 2)\sqrt{k})$ that $r < 3/(\sqrt{6} + 1) < 1$, which means that the requirement of $\|\mathbf{b}\|_2$ in Corollary 1' is more relaxed.

Second, the requirement of δ_{k+1} in Corollary 1' is more relaxed. Because μ in Corollary 1' is optional, it can be chosen small enough that

$$1/(1 + (\sqrt{6} + 2)\sqrt{k}) < (1 - \mu)/(\sqrt{k} + 1).$$

Despite the difference in requirements, the recovery errors given in Theorem 2 in [25] and Corollary 1' are the same, since these errors are both derived when the support set of the sparse signal is perfectly recovered.

In [40], the main result concerns the error estimation for OMP. It is proved that

$$\|\mathbf{x} - \text{OMP}_S \mathbf{x}\|_2^2 \leq 2\|\mathbf{x}\|_2 (\sigma_S(\mathbf{x}) + 4\delta(2 + \lceil \log_2 S \rceil) \|\mathbf{x}\|_2),$$

where $\mathbf{x}$ is a non-sparse signal we wish to recover, $\text{OMP}_S \mathbf{x}$ is the estimated solution via OMP in the S th iteration, $\sigma_S(\mathbf{x})$ is the ℓ_2 error between the best S -term approximation of $\mathbf{x}$ and $\mathbf{x}$, and δ is the RIC of order $2S$. This conclusion gives an upper bound on the error between the original signal and the estimated result of any iteration in OMP.

The original signal to be recovered in [40] is non-sparse, and the inputs $\mathbf{y}$ and Φ are assumed non-perturbed. Thus the result actually gives an upper bound on the error between $\mathbf{x}$ and $\text{OMP}_S \mathbf{x}$ for (N_0) process. Set $S = k$, and this result can be written as

$$\|\mathbf{x} - \hat{\mathbf{x}}\|_2^2 \leq 2\|\mathbf{x}\|_2 \left(\|\mathbf{x}^{(2)}\|_2 + 4\delta_{2k}(2 + \lceil \log_2 k \rceil) \|\mathbf{x}\|_2 \right). \quad (56)$$

In Corollary 2, the result is

$$\|\mathbf{x}^{(1)} - \hat{\mathbf{x}}\|_2 \leq \frac{\sqrt{1 + \delta_k}}{\sqrt{1 - \delta_k}} (\beta + \gamma) \|\mathbf{x}^{(1)}\|_2. \quad (57)$$

Before comparison, it is worth mentioning that there are fundamental differences between the above two conclusions. First, the non-sparse signal considered in this paper is almost sparse, whereas the one in [40] is arbitrary. Second, conditions that guarantee the support set recovery of the head of $\mathbf{x}$ is the main concern in Corollary 2, and based on the successful support recovery, an upper bound on the error is estimated. In the reference, however, the ℓ_2 error is directly given regardless of the support recovery. In some practical applications, recovering the support set other than the more accurate estimation is a fundamental concern [35], [38].

Despite the differences, a comparison of their recovery error estimations is given as follows. Notice that it is really hard to demonstrate which result is better, since the result in [40] involves δ_{2k} which does not appear in our work. However, a condition with δ_{2k} involved is given under which (56) is not better than (57). From (57) one has

$$\begin{aligned} \|\mathbf{x} - \hat{\mathbf{x}}\|_2^2 &= \|\mathbf{x}^{(1)} - \hat{\mathbf{x}}\|_2^2 + \|\mathbf{x}^{(2)}\|_2^2 \\ &\leq \frac{1 + 0.5}{1 - 0.5} (\beta + \gamma)^2 \|\mathbf{x}^{(1)}\|_2^2 + \|\mathbf{x}^{(2)}\|_2^2 \\ &= (3(\beta + \gamma)^2 + \beta^2) \|\mathbf{x}^{(1)}\|_2^2 \\ &\leq 4(\beta + \gamma)^2 \|\mathbf{x}^{(1)}\|_2^2. \end{aligned} \quad (58)$$

If $\delta_{2k} > (\beta + \gamma)^2/4$, from (58) one has

$$\|\mathbf{x} - \hat{\mathbf{x}}\|_2^2 < 16\delta_{2k} \|\mathbf{x}^{(1)}\|_2^2 \leq 16\delta_{2k} \|\mathbf{x}\|_2^2. \quad (59)$$

Compared with (56), (59) actually gives a tighter bound. Besides, the above requirement of δ_{2k} can be written in terms of k , i.e.,

$$\delta_{2k} \geq 1/(54k). \quad (60)$$

Assume nontrivially that $\beta + \gamma \neq 0$. Thus $|\text{supp}(\mathbf{x}^{(1)})| = k$ and $\|\mathbf{x}^{(1)}\|_2 \geq \sqrt{k} t_0$. According to (17) and (23), one has

$$\beta + \gamma \leq \frac{t_0}{3.69 \|\mathbf{x}^{(1)}\|_2} \leq \frac{1}{3.69 \sqrt{k}}. \quad (61)$$

Combining (58), (60) and (61), it holds that

$$\|\mathbf{x} - \hat{\mathbf{x}}\|_2^2 < 16\delta_{2k} \|\mathbf{x}^{(1)}\|_2^2 < 16\delta_{2k} \|\mathbf{x}\|_2^2. \quad (62)$$

VI. CONCLUSION

In this paper, considering a completely perturbed scenario in the form of $\tilde{\mathbf{y}} = \Phi \mathbf{x} + \mathbf{b}$ and $\tilde{\Phi} = \Phi + \mathbf{E}$, the performance of OMP in recovering an almost sparse signal, i.e. $\hat{\mathbf{x}} = R_{\text{OMP}}(\tilde{\mathbf{y}}, \tilde{\Phi}, \dots)$, is studied.

Though exact recovery of the head of $\mathbf{x}$ is no longer realistic, Theorem 1 shows that exact recovery of its support via OMP can be guaranteed under suitable conditions. Based on RIP, such conditions involve the sparsity, the relative perturbations of $\mathbf{y}$ and Φ , and the smallest nonzero entry of $\mathbf{x}$. Furthermore, the error between the the head of $\mathbf{x}$ and the output $\hat{\mathbf{x}}$ is estimated. This completely perturbed framework extends the prior work in non-perturbed scenarios. Furthermore, we construct a sensing matrix and perturbations with which an almost sparse signal cannot be recovered. The RIC of the matrix is slightly bigger than that in the sufficient condition of Theorem 1, which indicates that the condition is rather tight.

In addition, when $\mathbf{x}$ is an α -strong-decaying signal, several extensions of Theorem 1 are put forward. Theorem 3 reveals that the requirement in Theorem 1 can be weaker to guarantee the exact recovery of support. Theorem 4 demonstrates that if α is large enough, the support is picked up in the order of its entries' magnitude. This advantage is of great significance in practical scenarios, since the larger entries are often more important than others, and recovery in order indicates that the algorithm is more stable. In the end, Theorem 5 discussed the other scenario of general perturbations, which is in the form of $\tilde{\mathbf{y}} = \tilde{\Phi}\mathbf{x} + \mathbf{b}$ and $\tilde{\Phi} = \Phi + \mathbf{E}$, with the recovery process written as $\hat{\mathbf{x}} = R_{\text{OMP}}(\tilde{\mathbf{y}}, \tilde{\Phi}, \dots)$. Please notice that several results similar to Theorem 2-4 are available for (N'_2) process, however, they are not included for conciseness.

VII. APPENDIX

A. Proof of Lemma 1:

Proof: First of all, see $\{x_i | i = 1, 2, \dots, l-m\}$ as $l-m$ constants, and define the function with variable $x \geq \alpha x_{l-m}$

$$g(x) = \left(\sum_{i=1}^{l-m} x_i^2 + b_m x^2 \right) / \left(\sum_{i=1}^{l-m} x_i + c_m x \right)^2,$$

where $b_m = \sum_{i=0}^{m-1} \alpha^{2i}$, $c_m = \sum_{i=0}^{m-1} \alpha^i$, $1 \leq m < l$. Then $g(x) \geq g(\alpha x_{l-m})$.

The proof lies in the fact that $g(x)$ can be written as

$$g(x) = \frac{b_m}{c_m^2} - \frac{2\eta}{c_m^2} \frac{y}{(y - \theta + \eta/b_m)^2},$$

where

$$\eta = \frac{b_m}{c_m} \sum_{i=1}^{l-m} x_i,$$

$$\theta = \left(\frac{b_m}{c_m^2} \left(\sum_{i=1}^{l-m} x_i \right)^2 - \sum_{i=1}^{l-m} x_i^2 \right) / \left(\frac{2b_m}{c_m} \sum_{i=1}^{l-m} x_i \right),$$

and $y = x + \theta$. Because $-\theta + \eta/b_m > 0$, $g(x)$ equals its minimum when

$$y^0 = -\theta + \eta/b_m, \quad (63)$$

which further infers that

$$x^0 = y^0 - \theta = \eta/b_m - 2\theta = \frac{c_m \sum_{i=1}^{l-m} x_i^2}{b_m \sum_{i=1}^{l-m} x_i}.$$

Because $x^0 \leq x_{l-m} < \alpha x_{l-m} \leq x$ and $g(x)$ is an increasing function when $x \geq x^0$, $g(x) \geq g(\alpha x_{l-m})$.

Lemma 1 is proved by induction. To begin with, let $m = 1$ and fix $\{x_i | i = 1, \dots, l-1\}$, then the above conclusion implies $f(x_1, \dots, x_{l-1}, x_l) \geq f(x_1, \dots, x_{l-1}, \alpha x_{l-1})$.

Furthermore, assume that

$$f(x_1, \dots, x_{l-m+1}, \dots, x_l) \geq f(x_1, \dots, x_{l-m+1}, \dots, \alpha^{m-1} x_{l-m+1}).$$

The above conclusion gives

$$f(x_1, \dots, x_{l-m}, x_{l-m+1}, \dots, \alpha^{m-1} x_{l-m+1}) \geq f(x_1, \dots, x_{l-m}, x, \dots, \alpha^{m-1} x) |_{x=\alpha x_{l-m}} = f(x_1, \dots, x_{l-m}, \dots, \alpha^m x_{l-m}).$$

Therefore, it can be inducted that $f(x_1, \dots, x_l)$ is no less than $f(x_1, \dots, \alpha^{l-1} x_1)$, which concludes the proof. ■

B. Proof of Lemma 2:

Proof: It can be concluded from (8), (9), and (39) that

$$\begin{aligned} \mathbf{h}^l &= \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \tilde{\mathbf{y}} = \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp (\tilde{\Phi}\mathbf{x}^{(1)} + \mathbf{e}) \\ &= \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{A}}_{\Lambda^{l-1}} \mathbf{x}^* + \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \mathbf{e} \\ &= \mathbf{h}_1 + \mathbf{h}_2, \end{aligned} \quad (64)$$

where $\mathbf{h}_1 = \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{A}}_{\Lambda^{l-1}} \mathbf{x}^*$, $\mathbf{h}_2 = \tilde{\mathbf{A}}_{\Lambda^{l-1}}^T \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \mathbf{e}$. Because $\|\mathbf{x}^*\|_0 + |\Lambda^{l-1}| + 1 \leq k + 1$, according to Lemma 3.3 in [23], for all $j \notin \Lambda^{l-1}$, it holds that

$$|\mathbf{h}_1(j) - \mathbf{x}^*(j)| \leq \frac{\tilde{\delta}_{k+1}}{1 - \tilde{\delta}_{k+1}} \|\mathbf{x}^*\|_2. \quad (65)$$

According to Lemma 3.2 in [23], for $j \notin \Lambda^{l-1}$,

$$\begin{aligned} \|\mathbf{h}_2(j)\| &= \langle \tilde{\mathbf{A}}_{\Lambda^{l-1}} \mathbf{e}_j, \tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \mathbf{e} \rangle \leq \sqrt{1 + \tilde{\delta}_{k+1}} \|\tilde{\mathbf{P}}_{\Lambda^{l-1}}^\perp \mathbf{e}\|_2 \\ &\leq \frac{1}{1 - \tilde{\delta}_{k+1}} \|\mathbf{e}\|_2 \leq \frac{\varepsilon_h}{1 - \tilde{\delta}_{k+1}}. \end{aligned} \quad (66)$$

Notice that the last inequality holds since $\|\mathbf{e}\|_2 \leq \varepsilon_h$, which has been given in the proof of Theorem 3. Combining (64), (65), (66), and triangle inequality, one finally gets

$$\begin{aligned} |\mathbf{h}^l(j) - \mathbf{x}^*(j)| &\leq |\mathbf{h}_1(j) - \mathbf{x}^*(j)| + |\mathbf{h}_2(j)| \\ &\leq \frac{\tilde{\delta}_{k+1} \|\mathbf{x}^*\|_2 + \varepsilon_h}{1 - \tilde{\delta}_{k+1}}. \end{aligned}$$

■

REFERENCES

- [1] R. Gribonval and S. Lesage, "A survey of sparse component analysis for blind source separation: principles, perspectives, and new challenges," *Proceedings of ESANN06*, Apr. 2006, pp. 323-330.
- [2] Y. Li, A. Cichocki, and S. Amari, "Sparse component analysis for blind source separation with less sensors than sources," *ICA2003*, Apr. 2003, pp. 89-94.
- [3] P. Bofill and M. Zibulevsky, "Underdetermined blind source separation using sparse representations," *Signal Processing*, vol. 81, no. 11, Nov. 2001, pp. 2353-2362.
- [4] F. Georgiev, F. Theis, and A. Cichocki, "Blind source separation and sparse component analysis of overcomplete mixtures," *Proceedings of ICASSP04*, May 2004, pp. 493-496.
- [5] D. L. Donoho, "Compressed Sensing," *IEEE Trans. Information Theory*, vol. 52, no. 4, Apr. 2006, pp. 1289-1306.
- [6] E. Candès, J. Romberg, and T. Tao, "Robust uncertainty principles: exact signal reconstruction from highly incomplete frequency information," *IEEE Trans. Information Theory*, vol. 52, no. 2, Jan. 2006, pp. 489-509.
- [7] E. Candès, "Compressive sampling," *Int. Congress of Mathematics*, 2006, pp. 1433-1452.
- [8] R. G. Baraniuk, "Compressive Sensing," *IEEE Signal Processing Magazine*, vol. 24, no. 4, Jul. 2007, pp. 118-124.
- [9] S. Kim, K. Koh, M. Lustig, S. Boyd, and D. Gorinevsky, "An interior-point method for large-scale ℓ_1 -regularized least squares," *IEEE Journal of Selected Topics in Signal Processing*, vol. 1, no. 4, Dec. 2007, pp. 606-617.
- [10] M. A. T. Figueiredo, R. D. Nowak, and S. J. Wright, "Gradient projection for sparse reconstruction: application to Compressed Sensing and other inverse problems," *IEEE Journal of Selected Topics in Signal Processing*, vol. 1, no. 4, Dec. 2007, pp. 586-597.
- [11] I. Daubechies, M. Defrise, and C. D. Mol, "An iterative thresholding algorithm for linear inverse problems with a sparsity constraint," *Communications on Pure and Applied Mathematics*, vol. 57, no. 11, Nov. 2004, pp. 1413-1457.

- [12] S. Chen, S. A. Billings, and W. Luo, "Orthogonal least squares methods and their application to non-linear system identification," *Int. J. Control*, vol. 50, no. 5, Nov. 1989, pp. 1873-1896.
- [13] Y. C. Pati, R. Rezaifar, and P. S. Krishnaprasad, "Orthogonal matching pursuit: recursive function approximation with applications to wavelet decomposition," *Conf. Rec. 27th Asilomar Conf. Sig., Sys., & Comput.*, vol. 1, Nov. 1993, pp. 40-44.
- [14] G. Davis, S. Mallat, and Z. Zhang, "Adaptive time-frequency decomposition," *Optical Eng.*, vol. 33, no. 7, Jul. 1994, pp. 2183-2191.
- [15] D. Needell and R. Vershynin, "Uniform uncertainty principle and signal recovery via regularized orthogonal matching pursuit," *Foundations of Computational Mathematics*, vol. 9, no. 3, 2009, pp. 317-334.
- [16] D. Needell and J. A. Tropp, "CoSaMP: iterative signal recovery from incomplete and inaccurate samples," *Applied and Computational Harmonic Analysis*, vol. 26, no. 3, May 2009, pp. 301-321.
- [17] W. Dai and O. Milenkovic, "Subspace pursuit for Compressive Sensing signal reconstruction," *IEEE Trans. Information Theory*, vol. 55, no. 5, May 2009, pp. 2230-2249.
- [18] T. Blumensath and M. E. Davies, "Iterative hard thresholding for Compressed Sensing," *Applied and Computational Harmonic Analysis*, vol. 27, no. 3, Nov. 2009, pp. 265-274.
- [19] E. J. Candès, J. Romberg, and T. Tao, "Stable signal recovery from incomplete and inaccurate measurements," *Communications on Pure and Applied Mathematics*, vol. 59, no. 8, Aug. 2006, pp. 1207-1223.
- [20] T. T. Cai, L. Wang, and G. Xu, "New bounds for restricted isometry constants," *IEEE Trans. Information Theory*, vol. 56, no. 9, Sept. 2010, pp. 4388-4394.
- [21] J. A. Tropp, "Greed is good: algorithmic results for sparse approximation," *IEEE Trans. Information Theory*, vol. 50, no. 10, Oct. 2004, pp. 2231-2242.
- [22] J. A. Tropp and A. C. Gilbert, "Signal recovery from random measurements via orthogonal matching pursuit," *IEEE Trans. Information Theory*, vol. 53, no. 12, Dec. 2007, pp. 4655-4666.
- [23] M. A. Davenport and M. B. Wakin, "Analysis of orthogonal matching pursuit using the restricted isometry property," *IEEE Trans. Information Theory*, vol. 56, no. 9, Sept. 2010, pp. 4395-4401.
- [24] E. Liu and V. N. Temlyakov, "Orthogonal super greedy algorithm and applications in compressed sensing," 2010, available online: <http://citeseerx.ist.psu.edu/viewdoc/summary?doi=10.1.1.154.2996>.
- [25] S. Huang and J. Zhu, "Recovery of sparse signals using OMP and its variants: convergence analysis based on RIP," *Inverse Problems*, vol. 27, no. 3, Mar. 2011.
- [26] A. K. Fletcher and S. Rangan, "Orthogonal matching pursuit: a brownian motion analysis," *IEEE Trans. Signal Processing*, vol. 60, no. 3, Mar. 2012, pp. 1010-1021.
- [27] Q. Mo and Y. Shen, "A remark on the Restricted Isometry Property in Orthogonal Matching Pursuit," 2012, available online: <http://arxiv.org/abs/1201.2733>.
- [28] D. L. Donoho, M. Elad, and V. N. Temlyakov, "Stable recovery of sparse overcomplete representations in the presence of noise," *IEEE Trans. Information Theory*, vol. 52, no. 1, Jan. 2006, pp. 6-18.
- [29] T. T. Cai, G. Xu, and J. Zhang, "On recovery of sparse signals via ℓ_1 minimization," *IEEE Trans. Information Theory*, vol. 55, no. 7, July 2009, pp. 3388-3397.
- [30] E. J. Candès, "The Restricted Isometry Property and its implications for Compressed Sensing," *Comptes Rendus Mathématique*, vol. 346, no. 9, Feb. 2008, pp. 589-592.
- [31] Z. B. Haim, Y. C. Eldar, and M. Elad, "Coherence-based performance guarantees for estimating a sparse vector under random noise," *IEEE Trans. Signal Processing*, vol. 58, no. 10, Oct. 2010, pp. 5030-5043.
- [32] L. Denis, D. A. Lorenz, and D. Trede, "Greedy solution of ill-posed problems: error bounds and exact inversion," *Inverse Problems*, vol. 25, no. 11, Nov. 2009.
- [33] D. Needell and R. Vershynin, "Signal recovery from incomplete and inaccurate measurements via regularized orthogonal matching pursuit," *IEEE Journal of Selected Topics in Signal Processing*, vol. 4, no. 2, Apr. 2010, pp. 310-316.
- [34] A. K. Fletcher, S. Rangan, and V. K. Goyal, "On-off random access channels: a compressed sensing framework," 2009, available online: <http://arxiv.org/abs/0903.1022>.
- [35] M. Mishali and Y. C. Eldar, "From theory to practice: sub-Nyquist sampling of sparse wideband analog signals," *IEEE Journal of Selected Topics in Signal Processing*, vol. 4, no. 2, Apr. 2010, pp. 375-391.
- [36] M. A. Herman and T. Strohmer, "General deviants: an analysis of perturbations in Compressed Sensing," *IEEE Journal of Selected Topics in Signal Processing*, vol. 4, no. 2, Apr. 2010, pp. 342-349.
- [37] M. A. Herman and D. Needell, "Mixed operators in Compressed Sensing," *2010 44th Annual Conference on Information Sciences and Systems*, Mar. 2010, pp. 1-6.
- [38] M. Mishali and Y. C. Eldar, "Reduce and boost: recovering arbitrary sets of jointly sparse vectors," *IEEE Trans. Signal Processing*, vol. 56, no. 10, Oct. 2008, pp. 4692-4702.
- [39] E. Candès and T. Tao, "Decoding by linear programming," *IEEE Trans. Information Theory*, vol. 51, no. 12, Dec. 2005, pp. 4203-4215.
- [40] P. Bechler and P. Wojtaszczyk, "Error estimates for orthogonal matching pursuit and random dictionaries," *Constructive Approximation*, vol. 33, no. 2, Apr. 2011, pp. 273-288.